



- ▶ Digital, Fully Addressable
- ▶ Instant Locating of Fault
- ▶ Dedicated Monitoring Software
- ▶ MODBUS/JBUS Connection

## Description

The FG-SYS digital unit is designed to be used with TTK digital sense cables for water, bases and acid leak detection.

**In the event of a fault on the sense cables (leak or cable break):**

**Primary responses from the FG-SYS unit:**

- An audible alarm is triggered, the indicator light changes from green to red and a relay is activated.
- The display on the panel shows the leak location (to the nearest 1 metre) and fault's details (type of fault, leak or cable break), with time and date.

**Secondary optional advanced responses:**

- Dedicated monitoring software: TOPSurveillance installed on a computer will show dynamic drawings highlighting the location of the faults;
- Report to the BMS via a JBUS/MODBUS protocol.

The FG-SYS digital unit will reset automatically once the leak or the default is cleared.

## Features & Benefits

### FEATURES

- Wall mounted.
- 3 outputs are available, can be used independently.
- Up to 120 lengths of sense cables can be managed independently by the unit.
- 30 events history log allows to track leaks and cable breaks.
- 2 interface types for connection to building management and process control systems:
  - Two independent serial interfaces, each of them can be set for RS232 or RS422/485.
  - 9 relay contacts: 8 configurable relays + 1 specific relay for power interruption.
  - 8 relay positions are defined by a LED indicator.
  - Total programmable relays.
- Password is required for security.

### BENEFITS

- Pin-point location of a leak (to 1 metre).
- Each sense cable is addressable and can be customized by assigning a specific identity and name.
- Multiple simultaneous leaks can be detected (120 cables = 120 alarms).
- Two different types of sense cables (for detecting water and acid liquids) can be connected on the same panel for a truly bespoke system.
- Cable break faults can be detected (to the nearest cable).
- When a cable break occurs, the system maintains its integrity and keeps monitoring all cables installed before that break.
- Compatible with existing monitoring systems (Trend BMS etc.)
- Extension and upgrade of the system is easy. No additional power source or zoning panels are required.
- Minimum maintenance required.

## Buttons Functions

"ACQ"	Allows manual acknowledgement of the audible alarm. This key is also used in the main menu and history record, to validate and to return to the previous screen.
"T"est	Launches the FG-SYS system test and cables scan. The display will show the numbers, names and lengths for each connected sensing cable.
"M"enu	Settings menu for cables names, date & time, sound alarm, relays, language, passwords and others. This menu is password protected.
"H"istory	Access to the events log registering the 30 last alarms sorted by date in a FIFO memory.

# Technical Data

<b>Compatibility</b>	Sense cables (digital): FG-EC, FG-AC Sense cables (analog through FG-DTCS box): FG-ECS, FG-ACS Diversion boxes: FG-DTC, FG-DTCS, FG-DCTL Accessories: TTK 8723 jumper cable, FG-CLC, FG-TMC
<b>Dimensions &amp; Weights</b>	W: 200mm H: 250mm D: 100mm Weight: 3kg
<b>Maximum Length of Sense Cable</b>	1800 meters (600 meters per circuit)
<b>Accuracy</b>	+/- 1 meter
<b>Operating Languages</b>	English, French, German
<b>Dimensions</b>	200x250x100mm (Wall mounted, F)
<b>Supply Voltage</b>	100-240VAC, 50/60Hz, 15W
<b>Working Temperature Range</b>	0°C to 50°C
<b>Working Humidity</b>	5% to 95% non-condensing
<b>Relay Types</b>	Single contact NO-NC
<b>Alarm Relays</b>	Eight programmable relays for leaks and/or breaks with status LED, plus one power fail relay
<b>Supported Protocol</b>	Modbus RS232, RS422, RS485, available on two independent interfaces
<b>Maximum Switching Voltage</b>	120 V AC and 220 V DC
<b>Maximum Switching Capacity</b>	60 VA or 30 W

## Digital Unit Status

- **Normal Operating Condition:** The FG-SYS digital unit doesn't detect any alarm.
- **Leak Detection:** a leak occurs on one of the monitored zones; a signal light turns to red, an audible alarm sounds, a de-energized relay is activated; the LCD display shows the time and date of the alarm with the area name and the leak location in metres.
- **Cable Break:** When the FG-SYS digital unit detects a circuit break on one of the monitored circuits; a signal light turns to red, an audible alarm sounds, a de-energized relay is activated; the LCD display shows the time and date of the alarm with the area name and the damaged cable number.

## Technical Information

### Terminal Block Wiring :

- Power: 100-240VAC 50/60Hz 15W. Power connector M+F.
- Circuits 1,2,3: 4 pts connector for leader cable FG-CLC.
- Relays: 8 relays with 3 pts connectors(COM, NO, NC) programmable.
- Serial interfaces 1&2: Screw terminals with RS232 or RS422/485 for JBUS/MODBUS communication to BMS, and for external relays or PC Computer.

## Identification Codes

<b>FG-SYS F (Wall Mounted)</b>	FG-SYS digital unit wall mounted in metal enclosure
<b>FG-EC, FG-AC</b>	Digital sense cables in 3m, 7m and 15m lengths
<b>Accessories</b>	
<b>FG-CLC</b>	Leader cable ( Belden ref. 8723 in 3.5m lengths)
<b>FG-TMC</b>	End termination plug
<b>FG-DTC</b>	"T" branch, diversion box
<b>FG-DTCS</b>	Addressable box for FG-ECS, FG-ACS sense cables
<b>FG-DCTL</b>	Digital cut to length diversion box

## Certificates



FG-SYS digital unit meets the requirements of all European Standards in EN 50081-1 (92) and EN 50082-1 (92) (report reference n° 8080612-CQPE/1 dated 14/09/1998)  
FG-SYS digital unit meets the TÜV requirements, according to IEC 61010-1/A2.  
FG-SYS leak detection and locating system is UL Listed.

All the connections in the FG-SYS digital unit must be done with the power supply switched off.  
Read carefully the installation procedure for the FG-SYS digital unit.

This brochure has been carefully prepared to ensure technical accuracy but is only intended for promotional use. TTK cannot guarantee that the information contained herein contains no errors or omissions, and hence does not accept responsibility related to the use of its equipment. TTK maintain its obligations set forth in the Standard Terms and Conditions of Sale and will not, under any circumstances, assume liability for any incidental damages, indirect or consequential, arising from the sale, resale, use or misuse of this project. The purchaser(s) accept their responsibility as the sole judge(s) of the adaptability of the product for the intended use.  
FG-SYS and TOPSurveillance are trademarks of TTK S.A.S. © TTK 2016

- **TTK Headquarters** / 19, rue du Général Foy / 75008 Paris / France / T : +33.1.56.76.90.10 / F : +33.1.55.90.62.15 / [www.ttk.fr](http://www.ttk.fr) / [ventes@ttk.fr](mailto:ventes@ttk.fr)
- **TTK UK Ltd.** / 3 Luke Street / London EC2A 4PX / United Kingdom / T : +44 207 729 6002 / F : +44 207 729 6003 / [www.ttkuk.com](http://www.ttkuk.com) / [sales@ttkuk.com](mailto:sales@ttkuk.com)
- **TTK Pte Ltd.** / #09-05, Shenton House, 3 Shenton Way / Singapore 068805 / T: +65.6220.2068 / M: +65.9271.6191 / F: +65-6220.2026 / [www.ttk.sg](http://www.ttk.sg) / [sales@ttk.sg](mailto:sales@ttk.sg)
- **TTK Asia Ltd.** / 2107-2108 Kai Tak Commercial Building / 317 Des Voeux Road Central / Hongkong / T: +852.2858.7128 / F: +852.2858.8428 / [www.ttkasia.com](http://www.ttkasia.com) / [info@ttkasia.com](mailto:info@ttkasia.com)
- **TTK Middle East FZCO** / Building 6EA, Office 510 PO Box 54925 / Dubai Airport Free Zone / UAE / T: +971 4 70 17 553 / M: +971 50 259 66 29 / [www.ttkuk.com](http://www.ttkuk.com) / [cgalmiche@ttk.fr](mailto:cgalmiche@ttk.fr)
- **TTK Deutschland GmbH** / Berner Strasse 34 / 60437 Frankfurt / Deutschland / T : +49(0)69-95005630 / F : +49(0)69-95005640 / [www.ttk-gmbh.de](http://www.ttk-gmbh.de) / [vertrieb@ttk-gmbh.de](mailto:vertrieb@ttk-gmbh.de)
- **TTK North America Inc** / 1730 St Laurent Boulevard Suite 800 / Ottawa, ON, K1G 5L1 / Canada / T : +1 613 566 5968 / [www.ttkcanada.com](http://www.ttkcanada.com) / [sbalatchev@ttkcanada.com](mailto:sbalatchev@ttkcanada.com)